

## LED BULB VIA RADIO

**INTELLIGENT LED BULB**

LED bulb with transceiver. This unit is designed to turn on/off via software or switch.

It can be installed anywhere and does not require additional components to communicate with unit control.

**FEATURES**

- 6W consumption
- Frequency: 868MHz bidirectional
- 25000 hours of life
- Auto pairing

**SYSTEM**

|              |                          |                |
|--------------|--------------------------|----------------|
| Frequency    | 868MHz                   |                |
| Signal range | Up to 30 meters (indoor) |                |
| Lumen        | Real white               | 350 lm (5000k) |
|              | Warm white               | 300 lm (3000k) |
| Life         | 25000 hours              |                |

**ELECTRICAL & ENVIRONMENTAL**

|                     |             |
|---------------------|-------------|
| Consumption         | 6W          |
| Working temperature | 0°C ~ +40°C |
| RH                  | 85% HR max. |

**PHYSICAL FEATURES**

|            |               |
|------------|---------------|
| Thread     | E27           |
| Dimensions | 156 x 51,3 mm |
| Weight     | 132 g         |